




RESOCOIL BANJO


contact microphone
for banjos

CONTENTS OF THE BOX



- A. Screw 4x25 mm
- B. Screw 4x12 mm
- C. Nut
- D. Washer
- E-F. Connector with pickup

POSITIONING




Clean the surface of the banjo skin under the bridge with a humid towel. As soon it is dry remove the double tape protection from the Pickup and glue it on the chosen position. The recommended position is as on the photo F.

If you have a Bridge with only two legs, glue it under the higher string. We supply the pickup with a simple 3M double tape attached on the bottom of the pickup. If you decide to remove the pickup and use it again on another instrument, you can simply use a normal double tape.


To do a professional work Schertler suggests to consult a craftman for the installation.

INSTALLATION (open back model)



Find the best position to place the connector on your banjo, drill a $\varnothing 5\text{mm}$ hole on your banjo side. Place the screw (A) into the hole and fix the Connector part (E) inside your banjo. Use a screwdriver to fix the parts firmly.

INSTALLATION (resonator model)



Put the screw into the connector hole and screw it. Place the connector on the resonator flange and let the screw pass through one flange hole. Fix the connector using the washer (D) and the nut (C).

ROUNDED RESONATOR:

On certain Banjo model the supplied connector can't be mounted on the resonator flange. You can connect your DYN-Banjo with an extra XLR cable (3 meters) supplied by Schertler.



TECHNICAL SPECIFICATIONS

- Mechanical decoupling: Butterworth 2nd order
- Nominal impedance: 380ohm / 1000Hz
- Frequency response: 40 to 12kHz
- Dynamic range: 139dB, 145dB typical
- Sensitivity: 20mV/g
- Sensitivity on instrument: ca. -25dBm
- Cable length: 300 mm
- Circuit mode: Balanced via XLR
- Connection: Suggested microphonic input channel via XLR cable

ALL SCHERTLER® PRODUCTS ARE COVERED BY A LIMITED TWO-YEAR WARRANTY (FROM THE DATE OF PURCHASE) AGAINST MANUFACTURES DEFECTS. DETAILS CAN BE OBTAINED FROM YOUR LOCAL DEALER/REPRESENTATIVE. SCHERTLER SA STRONGLY BELIEVES IN "COMMON SENSE" AND THUS, MISUSE OF OUR PRODUCTS ARE NOT COVERED UNDER RIGHTS OBTAINED THROUGH OUR WARRANTY POLICY OR THAT OF INTERNATIONALLY RECOGNIZED TERMS AND CONDITIONS.

SCHERTLER SA IS CONSTANTLY AIMING TO IMPROVE ITS RANGE OF PRODUCTS THEREFORE, SCHERTLER SA RESERVES THE RIGHT TO AMEND PRODUCT SPECIFICATIONS WITHOUT NOTICE.

THE SCHERTLER® NAME/LOGO ARE REGISTERED TRADE-NAMES/ TRADEMARKS OF SCHERTLER SA, SWITZERLAND. ALL SCHERTLER® PRODUCTS ARE OF PROPRIETARY TECHNOLOGY AND COVERED BY ONE OF MORE WORLDWIDE PATENTS.



SCHERTLER®

ACOUSTIC AMPLIFICATION

SWISS MADE | schertler.com



TEL+41916300710

FAX+41916300711

info@schertler.com

SCHERTLER SA

Via Beroldingen 18

6850 Mendrisio